



# Smart Asset Tag



## Description

Attach Noccela Smart Asset tag to products and assets to track them with high accuracy and low latency. Noccela Smart Asset tag is an indoor positioning tag which also functions as an EAS tag in retail. Its compact and light design allows it to be attached to almost anything. It has been engineered to be highly reliable and secure.

## Features

- Up to cm accuracy
- Low power usage — typical battery life of 1 ~ 5 years depending on usage and environment
- Replaceable batteries
- Compact design — light and small enough to be attached to almost anything
- Easy to attach — use a EAS spike, double sided tape, magnet or a wire of which the length is typically 130 mm ~ 2000 mm (5.1 in ~ 78.7 in)
- Secure and reliable

## Technical Specifications

|                        |   |
|------------------------|---|
| Dimensions (L x W x H) | 56.46 x 66.73 x 20.94 mm (2.22 x 2.63 x 0.82 in)            |
| Environment            | Indoor, operating temperature 0 °C ~ 50 °C (32 °F ~ 122 °F) |
| Weight                 | 34 g (0.079 lb) without batteries                           |
| Attachment             | With a pin, wire, magnet or double-sided tape               |
| Detachment             | Pin and wire are detached with an EAS magnet                |
| Battery                | Two replicable LR03 (AAA) batteries                         |
| Radio                  | UWB   |
| Antenna Type           | Integral  |
| Certifications         | CE , FCC, & ISED (pending)                                  |